

新产品测试表 型号: ZP15-S15新PCB 1253IC+2.2M电阻

日期: 2019-8-8

制表: 曾德红

输入电压	输入电流	输入功率	输出负载		输出电压	效率	纹波	短路启动/过流点	VCC电压	负载调整率	电压调整率	电压精度	备注
90V			空载		15.03				14.39	0.00%	0.07%	0.20%	
	0.041	1.91	10%	0.10	15.03	78.7%	48	OK	14.98				
	0.073	3.59	20%	0.20	15.03	83.7%	24	OK	14.66				
	0.103	5.25	30%	0.30	15.03	85.9%	26	OK	14.72				
	0.134	6.95	40%	0.40	15.03	86.5%	28	OK	14.77				
	0.164	8.64	50%	0.50	15.03	87.0%	30	OK	14.82				
	0.193	10.3	60%	0.60	15.03	87.6%	34	OK	14.88				
	0.223	12	70%	0.70	15.03	87.7%	40	OK	14.94				
	0.253	13.8	80%	0.80	15.03	87.1%	40	OK	15.01				
	0.284	15.5	90%	0.90	15.03	87.3%	44	OK	15.08				
0.313	17.3	100%	1.00	15.03	86.9%	46	OK 1.9A 0W	15.15					
115V			空载		15.03				14.35	0.00%	0.07%	0.20%	
	0.034	1.91	10%	0.10	15.03	78.7%	35	OK	14.98				
	0.059	3.56	20%	0.20	15.03	84.4%	20	OK	14.6				
	0.084	5.25	30%	0.30	15.03	85.9%	28	OK	14.72				
	0.11	6.91	40%	0.40	15.03	87.0%	30	OK	14.76				
	0.131	8.58	50%	0.50	15.03	87.6%	38	OK	14.8				
	0.154	10.2	60%	0.60	15.03	88.4%	40	OK	14.85				
	0.178	11.9	70%	0.70	15.03	88.4%	42	OK	14.9				
	0.2	13.6	80%	0.80	15.02	88.4%	40	OK	14.99				
	0.224	15.3	90%	0.90	15.02	88.4%	44	OK	15.05				
0.24	17	100%	1.00	15.02	88.4%	46	OK 2A 0.37W	15.12					
230V			空载		15.03				14.36	0.00%	0.07%	0.20%	
	0.017	1.89	10%	0.10	15.03	79.5%	60	OK	14.76				
	0.03	3.54	20%	0.20	15.03	84.9%	68	OK	14.73				
	0.042	5.15	30%	0.30	15.03	87.6%	46	OK	14.76				
	0.054	6.72	40%	0.40	15.03	89.5%	42	OK	14.75				
	0.065	8.33	50%	0.50	15.03	90.2%	46	OK	14.8				
	0.076	10	60%	0.60	15.03	90.2%	48	OK	14.84				
	0.087	11.4	70%	0.70	15.03	92.3%	48	OK	14.88				
	0.098	13.1	80%	0.80	15.03	91.8%	50	OK	14.94				
	0.109	14.8	90%	0.90	15.03	91.4%	52	OK	15				
0.119	16.3	100%	1.00	15.03	92.2%	58	OK 2.4A 1.46W	15.07					

