

# 广州中逸光电子科技有限公司

## 测试报告

型号: AES04-220S05

日期: 2019-8-24

制表: 曾德红

### 测试数据:

输入电压	输入电流	输入功率	输出负载		输出电压	效率	纹波	短路启动	过流点	负载调整率	电压调整率	电压精度	结果
185v			空载		4.98		360		1.4A				P符合技术手册要求 <input type="checkbox"/> 不符合技术手册要求
	0.01	0.9	10%	0.08	4.77	44.3%	56	OK					
	0.015	1.4	20%	0.16	4.77	54.5%	64	OK					
	0.02	1.93	30%	0.24	4.79	59.3%	80	OK					
	0.025	2.48	40%	0.32	4.81	61.8%	96	OK					
	0.03	3.02	50%	0.40	4.83	63.7%	90	OK					
	0.035	3.58	60%	0.48	4.85	64.8%	80	OK					
	0.04	4.14	70%	0.56	4.87	65.6%	80	OK					
	0.045	4.72	80%	0.64	4.9	66.0%	110	OK					
	0.05	5.29	90%	0.72	4.92	66.7%	120	OK					
0.055	5.83	100%	0.80	4.95	67.5%	115	OK						
230V			空载		4.95		270	OK	1.2A	4.03%	0.81%	-0.80%	
	0.009	0.92	10%	0.08	4.76	43.0%	68	OK					
	0.013	1.45	20%	0.16	4.76	52.5%	84	OK					
	0.018	2	30%	0.24	4.78	57.4%	96	OK					
	0.022	2.49	40%	0.32	4.81	61.8%	90	OK					
	0.026	3.12	50%	0.40	4.83	61.9%	90	OK					
	0.03	3.6	60%	0.48	4.85	64.7%	90	OK					
	0.035	4.21	70%	0.56	4.87	64.8%	95	OK					
	0.04	4.81	80%	0.64	4.9	65.2%	96	OK					
	0.044	5.4	90%	0.72	4.93	65.7%	89	OK					
	0.048	5.99	100%	0.80	4.96	66.2%	92	OK					

